



## PORTABLE GASOLINE GENSET

### Continuous Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a constant electrical load. Average load can be 100%. The generator must not be overloaded.

### Standby Power

The maxpower available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utility power outage or under test conditions for up to 200 hrs of operation per year under average of 70%load.Overloading isn't permissible.

### Prime Power

The maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load. Average load should be 70%. The generator can be overloaded 10% for 1 hour per 12 hrs.

### Genset

Standby	kVA	12.5
Prime	kVA	11.3
Start System		Electric Start
Alternator		NSM Saccardo
Voltage		220 or 380(50Hz)
Fuel Type		Gasoline
Fuel Tank Capacity	lt	20

### Engine

Model		3854
Hp		21
Bore / Stroke	mm	75,5x70
Number of Cylinder / Type		2 / V Twin
Displacement	cc	627
Oil Capacity	lt	1.7
Engine Type		4-Stroke, Air Cooled

### Size

Weight	kg	145
L x W x H	cm	78x73x77